

3A,50-1000V High Efficient Rectifiers

Features

- Low leakage current
- Low forward voltage drop
- Glass passivated chip junction
- Moisture sensitivity: level 1, per J-STD-020
- Halogen-free according to IEC 61249-2-21 definition
- High temperature soldering guaranteed: 260°C/10 seconds



Applications

For use of fast switching rectification in lighting, cellular phone, portable device, power supplies and other consumer applications.

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)									
Parameter	Symbol	HS3A	HS3B	HS3D	HS3G	HS3J	HS3K	HS3M	Unit
Maximum repetitive peak reverse voltage	Vrrm	50	100	200	400	600	800	1000	V
Maximum RMS voltage	VRMS	35	70	140	280	420	560	700	V
Maximum DC blocking voltage	V _{DC}	50	100	200	400	600	800	1000	V
Maximum average forward rectified current	IF(AV)	3				А			
Peak forward surge current,8.3ms single half sine- wave superimposed on rated load per diode	IFSM	125				A			
Operating junction temperature range	TJ	-55 to +150			°C				
Storage temperature range	Tstg	-55 to +150				°C			

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)							
Parameter	Symbol	Тур	Unit				
Thermal Resistance, Junction to Ambient	R _{θJA}	65	°C /W				
Thermal Resistance, Junction to Case	Rejc	10	°C /W				
Thermal Resistance, Junction to Lead	R _{θJL}	15	°C /W				



Electrical Specifications (TA=25°C unless otherwise noted)												
Parameter	Symbol	Test Conditions	HS3A	HS3B	HS3D	HS3G	HS3J	НЅЗК	HS3M	Unit		
Forward Drop , Voltage	VF	l⊧=3A T _A =25℃	1.0 1.3 1.7						v			
	VF	l⊧=3A T _A =125℃	1.15							V		
Reverse leakage I _R current @V _R	1-	TJ =25℃	5						uA			
	IR	T _J =125℃	50									
Typical junction capacitance	CJ	4.0 V 1 MHZ	27.3				pF					
Maximum reverse recovery time	trr	I _F =0.5A,										nS
		I _R =1.0A, I _{RR} =0.25A		50					75			

Note:

1. Mounted on copper pad area of 8.0 x 8.0mm to each terminal.



Ratings and Characteristics Curves





Figure 5. Typical Instantaneous Forward Characteristics



Package Outline Dimensions

in inches (millimeters)

SMC (DO-214AB)



.000(.00)

.320(8.13) .305(7.75)

Revision History

.030(.76)

Document Version	Date of release	Description of changes
Rev.A	2021.06.01	Released Datasheet
Rev.B	2023.10.20	Modify document format



Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any thirdparty's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.