

GOOD-ARK Electronics

2A,50-1000V Fast Recovery Rectifiers

Features

- Low leakage current
- Low forward voltage drop
- Glass passivated chip junction
- Moisture sensitivity: level 1, per J-STD-020
- Halogen-free according to IEC 61249-2-21 definition
- High temperature soldering guaranteed: 260°C/10 seconds



eSGB (DO-221AC)

Applications

For use of fast switching rectification in lighting, cellular phone, portable device, power supplies and other consumer applications.

Maximum Ratings & Electrical Characteristics(TA=25°C unless otherwise noted)									
Parameter	Symbol	L2F1	L2F2	L2F3	L2F4	L2F5	L2F6	L2F7	Unit
Maximum repetitive peak reverse voltage	VRRM	50	100	200	400	600	800	1000	V
Maximum RMS voltage	V _{RMS}	35	70	140	280	420	560	700	V
Maximum DC blocking voltage	V_{DC}	50	100	200	400	600	800	1000	>
Maximum average forward rectified current	I _{F(AV)}	2					А		
Peak forward surge current,8.3ms single half sine- wave superimposed on rated load per diode	I _{FSM}	60					Α		
Operating junction temperature range	TJ	-55 to +150					°C		
Storage temperature range	T _{STG}	-55 to +150					°C		

Thermal-Mechanical Specifications (TA=25°C unless otherwise noted)							
Parameter	Symbol	Тур	Unit				
Thermal Resistance, Junction to Ambient	R _{0JA}	85	°C/W				
Thermal Resistance, Junction to Case	Rejc	15	°C/W				
Thermal Resistance, Junction to Lead	Rejl	18	°C/W				



Electrical Specifications(TA=25°C unless otherwise noted)										
Parameter	Symbol	Test Conditions	L2F1	L2F2	L2F3	L2F4	L2F5	L2F6	L2F7	Unit
Forward Drop Voltage	V _F	I _F =2A	1.3						V	
Reverse	IR	T _J =25°C	5						- uA	
leakage I current @V _R	IR	T _J =125°C	50							
Typical junction capacitance	CJ	4.0 V 1 MHZ	11					pF		
Maximum reverse recovery time	trr	I _F =0.5A, I _R =1.0A, I _{RR} =0.25A	150 250 500						nS	

Note:

1. Mounted on copper pad area of 0.2x0.2" (5.0 x 5.0mm) to each terminal.



Ratings and Characteristics Curves

(TA = 25°C unless otherwise noted)




Figure 1.Forward Current Derating Curve




Figure 3. Typical Reverse Characteristics




Figure 5. Typical Junction Capacitance




Figure 2.Maximum Non-Repetitive Peak Forward Surge Current




Figure 4. Typical Instantaneous Forward Characteristics




GOOD-ARK Electronics

Package Outline Dimensions


in inches (millimeters)


eSGB (DO-221AC)












Soldering footprint



Revision History

Document Version	Date of release	Description of changes
Rev.A	2021.06.01	Released Datasheet
Rev.B	2023.10.12	Modify document format
Rev.C	2023.12.29	Modify package name

L2F1 thru L2F7

GOOD-ARK Electronics

Disclaimers

These materials are intended as a reference to assist our customers in the selection of the Suzhou Good-Ark product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Suzhou Good-Ark Electronics Co., Ltd.or a third party.

Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.

All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Suzhou Good-Ark Electronics Co., Ltd. without notice due to product improvements or other reasons. It is therefore recommended that customers contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized Suzhou Good-Ark Electronics Co., Ltd. for the latest product information before purchasing a product listed herein. The information described here may contain technical inaccuracies or typographical errors. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors. Please also pay attention to information published by Suzhou Good-Ark Electronics Co., Ltd. by various means, including our website home page. (http://www.goodark.com)

When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, Please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Suzhou Good-Ark Electronics Co., Ltd. assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.

The prior written approval of Suzhou Good-Ark Electronics Co., Ltd. is necessary to reprint or reproduce in whole or in part these materials.

Please contact Suzhou Good-Ark Electronics Co., Ltd. or an authorized distributor for further details on these materials or the products contained herein.